



Trusted Zero Client Atrust w200

- 1 Power LED**
Indicates the status of power.
- 2 Power Button**
Press to turn on/off the client.
- 3 Audio Combo**
Headphone / Microphone Combo.
- 4 USB-C Port (USB 3.2 Gen 1)**
Connects to a USB device.
- 5 USB-A Port (USB 2.0) x 2**
Connects to a USB device.
- 6 Kensington Security Slot**
Connects to a Kensington security lock.
- 7 Dual-Mode Displayport x 2**
Connects to a monitor.
- 8 USB-A Port (USB 3.2 Gen 1) x 2**
Connects to a USB device.
- 9 USB-A Port (USB 2.0) x 2**
Connects to a USB device.
- 10 LAN Port**
Connects to a host server through a LAN switch.
- 11 DC IN**
Connects to an AC adaptor.



Atrust w200

- ▶ Dual display support
- ▶ Durable and quiet design
- ▶ Simplified management
- ▶ Low power consumption
- ▶ Lower total cost of ownership (TCO)

Atrust w200

Processor	AMD Ryzen™ Embedded R2312 (Manufacturing option : R2314)
Memory	
System memory	DDR4 8 GB (Dual channels)
Storage	eMMC 32 GB
Graphics	
Maximum resolution	Up to 3840 x 2160 @ 60Hz
I/O Interfaces	
I/O ports	Front : 2 x USB-A Port (USB 2.0), 1 x USB-C Port (USB 3.2 Gen 1), 1 x Audio Combo Rear : 2 x Dual-Mode Displayport, 2 x USB-A Port (USB 2.0), 2 x USB-A Port (USB 3.2 Gen 1), 1 x LAN Port, 1 x DC IN, 1 x Kensington Security Slot * USB3.2 Gen1 Type-C port did not support display function
Networking	
Ethernet	10 M / 100 M / 1 G
WiFi	802.11 a / b / g / n / ac (Manufacturing option, Planned to release in 2025/Q1)
Dimensions / Weight	
Dimensions	(W) 39.5 x (D) 103 x (H) 143 mm
Weight	466 g (approximate)
Environment	
Operating temperature	0°C ~ 35°C
Non-operating temperature	-20°C ~ 60°C
Operating humidity (Rh)	10% ~ 90% (non-condensing)
Non-operating humidity (Rh)	5% ~ 95% (non-condensing)
Power	
Operating voltage range	100 ~ 240 VAC
Rated line frequency	50 ~ 60 Hz
AC Adaptor	+19V DC, 2.1A
Software	
Operating System	Trusted Zero Client
Management	ADM (Atrust Device Manager)
Protocols	PCoIP / PCoIP Ultra
Security	
TPM	dTPM 2.0

© 2024 Atrust Computer Corp. The information contained herein is subject to change without notice. Atrust shall not be liable for technical or editorial errors or omissions contained herein. Teradici, PCoIP, and PCoIP Ultra are trademarks of HP Inc. AMD is a trademark of Advanced Micro Devices.. Inc. To learn more, visit www.atrustcorp.com.



Atrust Computer Corp.

3F., 361, Fusing 1st Rd., Gueishan Dist., Taoyuan City 333, Taiwan
T.+886-3-3288837 F.+886-3-3288973
sales@atrustcorp.com www.atrustcorp.com